



Page:	3-1
Date:	2017-MAY-05
Revision:	7.1
Supersedes:	Revision 7, 2015-MAR-01

---

## SPECIFICATIONS FOR NEW UNDERGROUND RESIDENTIAL DISTRIBUTION SYSTEMS

---

### 3.0 URD DESIGN GUIDELINES

#### 3.1 Overview of ATCO Electric's URD System Design

The power supply to all single lot underground residential services is through front lot service. Single phase transformers are connected to secondary pedestals, which in turn provide the connection to the residential service. The secondary design provides looping of the secondary conductors between the service pedestals. This allows more efficient and responsive restoration of service to customers in the event of an outage.

Appendix C, Drawings C.1.2A and C.1.2B illustrate a typical front lot service with the subdivision primary and secondary pedestal cable and secondary service cable connections. The supply is at 120/240 volts.

Note: For Single Family Dwellings, with the exception of commercial customers fed from a separate transformer, all secondary services are served from a secondary pedestal connected to a transformer.

#### 3.2 Landscaping Adjacent to Underground Electrical Equipment

Before commencing the design of a URD system, the Developer and/or its agent(s) must confirm landscaping plans for all vegetation in the area with the Municipal Authority (see Appendix D, DrawingD.1.0 for required clearances to equipment).

#### 3.3 URD Design

This section outlines the responsibilities and standards for design of an underground electrical distribution development. It is intended to assist the Developer and/or its agent(s) in preliminary design discussions with ATCO Electric's Engineering Representative.

##### 3.3.1 Design Responsibilities

ATCO Electric is responsible for planning and designing the express and source primary feeders which supply a URD. In addition, ATCO Electric is

Page:	3-2
Date:	2017-MAY-05
Revision:	7.1
Supersedes:	Revision 7, 2015-MAR-01

## **SPECIFICATIONS FOR NEW UNDERGROUND RESIDENTIAL DISTRIBUTION SYSTEMS**

---

responsible for the planning, design, construction, installation and termination of three phase switch cubicle facilities.

ATCO Electric's Engineering Representative will, at the request of the Developer and/or its agent(s), provide:

- a) information on the switch cubicle requirements (dimensions, schedule and locations); and
- b) the System Planning Study for the development area.

Appendix D, Drawing D.2.4 is a schematic representation of the facilities ATCO Electric and the Developer are each responsible to provide and install.

### **3.3.2 Design Standards**

All underground electrical distribution facilities must be designed in accordance with ATCO Electric's standards as outlined in this specifications document. Adherence to the planning and design standards ensures ATCO Electric is able to maintain required service levels.

#### **3.3.2.1 Primary System Design**

Where the planning study by ATCO Electric determines that Primary System Looping is required for the development, the Developer and/or its agent(s) must include a primary looped system in the design that is submitted for ATCO Electric approval.

Subdivision development may proceed in several phases and time frames. As such, arrangements for temporary looping and/or extension to future phases must be considered. Decisions regarding the system configuration at the boundary limits must be discussed with ATCO Electric's Engineering Representative prior to design submission. Options to be considered include:

- a) creation of a underground loop (reusable for future phase);

Page:	3-3
Date:	2017-MAY-05
Revision:	7.1
Supersedes:	Revision 7, 2015-MAR-01

## **SPECIFICATIONS FOR NEW UNDERGROUND RESIDENTIAL DISTRIBUTION SYSTEMS**

---

b) creation of a temporary loop (overhead or underground);

**Note:** Designs for a URD shall minimize splices wherever possible. There should be no splices within the boundary of any project. Each unnecessary splice introduces another element which can fail and degrade the performance of the system.

### **3.3.2.2 Secondary System Design**

The design proposed by the Developer and/or its agent(s) must include secondary looping between pedestals (see Appendix C, Drawing C.1.2A). In the event of a secondary system failure, each pedestal must have an alternate source of supply.

This is applicable for urban design only. Rural secondary looping is at the discretion of the developer.

Loads should typically be fed from the nearest secondary pedestal (ie – streetlights). It is discouraged to run secondary from one pedestal past another pedestal to feed a streetlight for example.

### **3.3.2.3 Street Light Design**

The Roadway Authority (typically the Municipality) will dictate the roadway lighting requirements. Refer to the Municipality’s most recent guidelines.

The Developer and/or its agent(s), unless directed otherwise by the governing authority, shall utilize the “Guide for the Design of Roadway Lighting” published by Transportation Association of Canada (TAC) 2006, as the **minimum requirement** for the design of safe roadway lighting.

The Developer and/or its agent(s) must confirm the roadway classifications with the Roadway Authority before submitting any detailed engineering design. Street lighting design calculations and

Page:	3-4
Date:	2017-MAY-05
Revision:	7.1
Supersedes:	Revision 7, 2015-MAR-01

---

## SPECIFICATIONS FOR NEW UNDERGROUND RESIDENTIAL DISTRIBUTION SYSTEMS

---

documentation must be submitted for ATCO Electric's acceptance at design review; the minimum requirements are described in Section 4.2.6. A sample of inputs and calculations utilizing AGI 32 is provided in Appendix C, Document C.1.5.

All designs must be based on a uniform tilt of zero degrees (0°) parallel to the road surface. In residential areas, street lights should be placed on lot lines, where practical. In subdivisions with curved roads and irregular lot sizes, alternate locations may have to be determined to meet lighting requirements. A street light will be fed from pedestals only.

See Appendix D, Drawings D.7.1 & D.7.2 for street light alignment details.

### 3.4 Performance Requirements

#### 3.4.1 Grounding

The Consulting Engineer is responsible to ensure all the requirements of the grounding system meet ATCO Electric's standards (see Appendix B, Drawings for details).

#### 3.4.2 Voltage Drop

The Consulting Engineer shall use the voltage drop calculator provided on ATCO Electric's website (see Appendix C, Report C.1.4 for Sample Voltage Calculation Report) to ensure:

- a) the voltage drop from the transformer secondary to all customer meters shall not exceed 3%; and,
- b) during a single contingency situation (i.e., the loss of a single phase padmount transformer, a subdivision primary feeder, etc.), the voltage drop from the transformer secondary to all customer meters shall not exceed 7.5%.

---

**SPECIFICATIONS FOR NEW UNDERGROUND RESIDENTIAL DISTRIBUTION SYSTEMS**

---

### 3.4.3 Transformer Loading

Tables 3.1, 3.2 and 3.3 identify the maximum number of 100 amp, 200 amp or a combination of 100/200 amp customers (services) that can normally be supplied from ATCO Electric’s standard single phase 14.4kV – 120/240V (nominal) rated primary and secondary loop-feed transformers to maintain the voltage within the limits identified in Section 3.4.2.

The number of services that can be supplied may be limited by size restrictions of the secondary compartments and/or the allowable secondary power cable voltage drop. ALL designs and calculations submitted must meet voltage and loading requirements.

**Table 3.1 - Maximum Number of 100 A Services Supplied by Padmount Transformers**

Transformer Size	100 A Services
50kVA	16
75kVA	24
100kVA	31

**Table 3.2 - Maximum Number of 200 A Services Supplied by Padmount Transformers**

Transformer Size	200 A Services
50kVA	8
75kVA	12
100kVA	15

**Table 3.3 - Maximum Number of a Combination of 100 A and 200 A Services Supplied by Padmount Transformers**

Transformer Size	100 A Services	200 A Services
50kVA	12	2
75kVA	16	4
100kVA	22	8

## 3.5 Design Detail

Page:	3-6
Date:	2017-MAY-05
Revision:	7.1
Supersedes:	Revision 7, 2015-MAR-01

---

## SPECIFICATIONS FOR NEW UNDERGROUND RESIDENTIAL DISTRIBUTION SYSTEMS

---

### 3.5.1 Cable Trench Alignments/Depths

Standard alignments and trenching specifications for underground power and other joint-use facilities are generally defined by the Municipal Authority. It is the responsibility of the Developer and/or its agent(s) to obtain the most current version of the Municipal Standards. Any deviations to the standard vertical or horizontal trench details must be approved by ATCO Electric's Engineering Representative prior to design submission. Refer to the drawings in Appendix D for details.

#### 3.5.1.1 Service Entry to Lot

For Single Family Dwellings (Urban only), service boxes and stakes are to be installed as per Appendix D Drawings. Service boxes must be installed on the non driveway side of the lot. The service cable coiled inside the service box shall be three quarters of the lot length up to a maximum of 30M of cable.

For Single Family Dwellings (rural only), secondary cables shall be stubbed on a meter post (or metering pedestal) 1.5m past the edge of the URW, and 1.5m from the lot line or edge of approach. This location selected must be accessible, with no obstructions (trees, bushes, etc).

For Multiple Family Dwellings, service boxes are not typically required as the secondary cables shall be stubbed a maximum of 1m from the building's foundation on the opposite side of the dwelling of the gas service

### 3.5.2 Primary and Secondary Cables

#### 3.5.2.1 Primary Cables

The only acceptable cable to be used for subdivision primary service is:  
1/C – #1 AWG TRXLPE compact aluminum strand 60% Cu  
concentric neutral

See Appendix E, Drawing E.1 for the primary cable information.

Page:	3-7
Date:	2017-MAY-05
Revision:	7.1
Supersedes:	Revision 7, 2015-MAR-01

---

**SPECIFICATIONS FOR NEW UNDERGROUND RESIDENTIAL DISTRIBUTION SYSTEMS**

---

**3.5.2.2 Secondary and Service Drop Cables**

The following cables are to be used for secondary service:

2/C - #2 600V aluminum conductor jacketed type USEB90  
reduced #6 Cu concentric neutral

2/C - 4/0 600V aluminum conductor jacketed type USEB90  
reduced #1 Cu concentric neutral

2/C - 300 MCM 600V aluminum conductor type USEB90 full size 300  
MCM Cu concentric neutral

See Appendix E, Drawing E.2 for the secondary cable information.

For Multiple Family Dwelling Services, the service conductor shall be  
2/C - 300 MCM Aluminium.

Page:	3-8
Date:	2017-MAY-05
Revision:	7.1
Supersedes:	Revision 7, 2015-MAR-01

## **SPECIFICATIONS FOR NEW UNDERGROUND RESIDENTIAL DISTRIBUTION SYSTEMS**

---

### **3.5.3 Switch Cubicles**

If a switch cubicle is required, the Developer and/or its agent(s) are responsible to propose a final location to be approved by ATCO Electric's Engineering Representative.

The switch cubicle must be located a minimum distance of 3.0m (see Appendix D, Drawing D.1.0) from the curb, and a 6.0m x 6.0m easement is required. If necessary, the Developer and/or its agent(s) will provide ATCO Electric with the easement (see Section 4.2.2).

**Note:** The distance from the curb must take into consideration the size and location of the base ground grid, which extends beyond the boundaries of a switch cubicle base (see Appendix B, E series of prints).

### **3.5.4 Padmount Transformers and Secondary Pedestals**

#### **3.5.4.1 Installation**

For the purposes of these specifications, padmount transformers will be single-phase, 14.4kV – 120/240V (nominal) rated primary and secondary, loop-feed transformers, and three-phase, 25kV – 120/208V or 347/600V (nominal) rated primary and secondary, loop-feed transformers.

Padmount transformers are to be installed as follows:

- a) The transformers must be mounted on pre-cast bases located at intersecting lot lines, and coordinated with other facilities located on the street so as not to encumber both lot lines of any residential family zoned lot.
- b) Transformers must :
  - i. not be installed onto pie-shape properties inside a cul-de-sac;
  - ii. not be set less than 6.0m from a cut corner;



Page:	3-9
Date:	2017-MAY-05
Revision:	7.1
Supersedes:	Revision 7, 2015-MAR-01

## **SPECIFICATIONS FOR NEW UNDERGROUND RESIDENTIAL DISTRIBUTION SYSTEMS**

---

- iii. not be located within 1.0m from any other utilities' above ground facilities and less than a 2.0m clearance to bus stops;
- iv. not be set in a sidewalk;
- v. not be placed on the driveway side of a lot;
- vi. be positioned so its access lid/door faces the direction as shown in Appendix D.
- vii. Be placed within a URW or a separate ATCO Electric easement obtained by the developer (minimum 3.0m x 3.0m for transformer)

Secondary Pedestals are to be installed as follows:

- a) When installing pedestals, it is recommended to pair pedestals with street lights to minimize facility locations and the visual impact to lot owners.
- b) When the pedestal is parallel to the road, the pedestal door faces the residence; this includes pedestal/transformer combinations and street light/pedestal combinations.
- c) When the pedestal is placed perpendicular to the road surface, the door shall be positioned so that the worker is facing oncoming traffic when accessing the pedestal.
- d) The pedestal must not be placed on the driveway side of a lot (If this cannot be avoided, ATCO Electric's CSR & Engineering representative should be consulted).

See Appendix D, Drawings for transformer and pedestal alignment, orientation and clearance details.

### **3.5.4.2 Equipment Identification**

Page:	3-10
Date:	2017-MAY-05
Revision:	7.1
Supersedes:	Revision 7, 2015-MAR-01

## **SPECIFICATIONS FOR NEW UNDERGROUND RESIDENTIAL DISTRIBUTION SYSTEMS**

---

The circuit and equipment identification and tagging requirements on the engineering drawings must match the identification and tags on the cables and equipment installed (see Appendix B, Drawing H9).

### **3.5.4.3 Grounding**

The Developer and/or its agent(s) are responsible, as part of the overall installation of the URD system, to complete the design, installation and interconnection of the grounding facilities at each piece of equipment (padmount transformer, secondary pedestal, street light, etc.) as per Drawings in Appendix B. The grounding materials must meet the requirements of Appendix E.5.

All conductive above-ground facilities (e.g., metal guard posts or bollards, stand-alone cable TV and communication pedestals, metering pedestals, etc.) within 3.0m of any electric utility facilities shall be bonded to the electric utility facilities' ground grid.

### **3.5.5 Primary Fusing**

ATCO Electric will complete the primary fuse coordination at the switch cubicle and supply the required on-site fuse units.

### **3.5.6 Street Lighting**

#### **3.5.6.1 Installation**

The street light is to be positioned as follows:

- Single Davit: Where possible, the access door is to be positioned so that the employee is facing oncoming traffic when working in the light standard.
- Double Davit installed on an island: The door is to be installed parallel to the road so that the employee has visibility of approaching traffic from either direction when working in the standard.

Page:	3-11
Date:	2017-MAY-05
Revision:	7.1
Supersedes:	Revision 7, 2015-MAR-01

---

**SPECIFICATIONS FOR NEW UNDERGROUND RESIDENTIAL DISTRIBUTION SYSTEMS**

---

**3.5.6.2 Standard Luminaires**

For residential street lighting, the standard davit pole is 9.0 m in height, and the davit arm is 2.0 m in length. If other davit poles or davit arms are required, please contact ATCO Electric's Engineering Representative. Design and installation of wooden poles will not be permitted under the URD process.

The design must only use the standard lamps or luminaire types for subdivisions, as per Appendix E, Drawing E.8B for the approved street light poles and parts.

Note that at the time of writing this, Fort McMurray uses a different LED street light head than the remainder of the province (not listed by default in Appendix E). Developers doing work in Fort McMurray should ensure they contact ATCO Electric for the latest details on LED street lighting heads. LED products can change fairly rapidly, so confirming the latest details on LED street lights with ATCO prior to ordering products is recommended.

---

**SPECIFICATIONS FOR NEW UNDERGROUND RESIDENTIAL DISTRIBUTION SYSTEMS**

---

**3.5.6.3 Photometric Files**

A standard AGI 32 template will be available on ATCO Electric’s website for those using AGI 32 for lighting design. (Click [HERE](#) to download)

Contractors not using AGI 32 are required to download the photometric files from ATCO Electric’s website and modify the files to match the standard luminaires in Section 3.5.6.2. (Click [HERE](#) to download)

**3.5.6.4 Design Task and Calculation Type**

The following table specifies the standard calculation type for each design task:

**Table 3.4: Standard Calculation Type**

<b>Design Task</b>	<b>Calculation Type</b>
<b>Straight Roadways</b>	Luminance
<b>Curved Roadways and Interchanges</b>	Illuminance
<b>Cul-de-Sacs</b>	Illuminance
<b>Sidewalks</b>	Illuminance
<b>Intersections</b>	Illuminance
<b>Crosswalks</b>	Illuminance
<b>Roundabouts</b>	Illuminance

For urban residential subdivisions, ATCO Electric requires calculations to be done on roadways and interchanges (straight and curved), cul-de-sacs, intersections and roundabouts. Sidewalks and crosswalks are not required unless otherwise specified or required by the Roadway Authority

## **SPECIFICATIONS FOR NEW UNDERGROUND RESIDENTIAL DISTRIBUTION SYSTEMS**

---

Lighting requirements for rural subdivisions are defined by the road authority.

### **3.5.6.5 Calculation Grids**

Separate calculation grids are required when the design task changes. This section discusses the grid settings required for each design task.

#### **3.5.6.5.1 Roadways and Interchanges**

- a) The calculation grid shall cover the entire road surface (curb-to-curb) unless the Roadway Authority states otherwise. It shall start and finish at a luminaire with all luminaires within the section covered in between.
- b) The left-to-right spacing between grid points is equal to the narrowest spacing between two luminaires in that section divided by 10, but may not exceed 5.0 m. The top-to-bottom points should be placed along the  $\frac{1}{4}$  point of the lane width for straight roads, and 2.0 m apart for curved roads.
- c) Symmetrical spacing (staggered, opposite and median lighting) requires calculation for all lanes in a single direction of travel. For single-sided spacing with two way traffic (divided by a yellow line or a median), a separate calculation should be undertaken for the lane(s) in each direction of travel. The worst case luminance/illumination and uniformity ratio for either direction shall take precedence.
- d) Curved roads with less than five degrees ( $5^{\circ}$ ) curve shall be treated as straight roads, and luminance calculation type shall be applied.

Page:	3-14
Date:	2017-MAY-05
Revision:	7.1
Supersedes:	Revision 7, 2015-MAR-01

---

**SPECIFICATIONS FOR NEW UNDERGROUND RESIDENTIAL DISTRIBUTION SYSTEMS**

---

**3.5.6.5.2 Cul-de-Sacs, Intersections and Roundabouts**

The grid points should be placed 2.0 m apart and take the shape of the area. The boundaries are determined by the end of curb return or cut corner.

**3.5.6.5.3 Sidewalks (If Required)**

Horizontal calculations for sidewalks should include a single line of grid points on the centreline of the sidewalk using the same grid as used for the roadway. If the sidewalk is over 2.0 m wide, additional rows of equally spaced grid points will be required. In all cases, each grid line should not be more than 1.0 m from the edge of the walkway. The horizontal grid should be at the surface grade of the sidewalk.

The vertical illuminance values should be calculated at a height of 1.5 m in the two directions parallel to the main pedestrian flow, along the centreline of the sidewalk using the roadway longitudinal grid, but not including grid points under the luminaires.

**3.5.6.5.4 Crosswalks (If Required)**

The calculation grid within the crosswalk is required on a vertical plane across the roadway at a height of 1.5 m, with calculation points spaced at 0.5m. Only a single line of calculation point is required. This calculation line should be centred in the crosswalk and extend from the curb line to the centreline of the roadway. The calculation direction should be towards the approaching driver. For intersection with multiple crosswalks, each crosswalk should be calculated separately.